FIRST TOUCH SCREEN Frequency Inverter



GEMAS ISAVER+

- Power consumption reading
- Modes (day/night/backwash)
- 4 Timer program
- 4 Models

WHAT'S A FREQUENCY INVERTER?


Frequency Inverter is a device that converts alternating current of one frequency to another frequency, the result of this conversion leads to a motor speed change in pool pump application.

The majority of pool pumps installed in the market now are single speed, they are quite powerful for heavy duties like backwash, but this is not constantly needed as in pumping or filtration, changes of motor speed on a single speed pump can meet different application demand for the pump.




80% ENERGY SAVING

With an iSAVER⁺, pump speed can be set to adapt for different operations, running cost will be dramatically reduced.



25% QUIETER

Running at low speed promises a much more pleasant user experience, sound level can be reduced by as much as 25%.




ADDED BENEFITS

Timer program

4 timers for 24-hour operation, each with an individual speed for different pool features, filtration or heating, better take advantage of electricity tariff at different time of day

Longer lifespan

Lower running speed means a reduction in wear, particularly in mechanical seals




Better filtration

Small particles can be removed easier when the water moves more slowly

Eco-friendly

Tremendous greenhouse gas emission decreased due to 80% reduction in electricity consumption

FEATURES



Touch Screen

- Classic touch control
- 4 timers program for 24 hours running
- User friendly interface with power consumption indication
- 35 running speeds from 1200 ~ 2900 RPM by increment of 50RPM

External Control

• Dry contacts reserved for different types of external control

SPECIFICATION

| Model | 01111NV1100 | 0111INV2200 | 0111INV1100C | 0111INV2200C |
|---------------------|--------------|--------------|--------------|--------------|
| Operation Condition | -10 ~ 40°C | -10 ~ 40°C | -10 ~ 40°C | -10 ~ 40°C |
| Input Power | 1ph AC | 1ph AC | 1ph AC | 1ph AC |
| Input Voltage | 220V~240V | 220V~240V | 220V~240V | 220V~240V |
| Frequency | 50 Hz | 50 Hz | 50 Hz | 50 Hz |
| Output Voltage | 1ph, 0~240V | 1ph, 0~240V | 3ph, 0~240V | 3ph, 0~240V |
| Output Power | Max 1.1kW | Max 2.2kW | Max 1.1kW | Max 2.2kW |
| Output Current | Max 6A | Max 12A | Max 4.5A | Max 8A |
| Pump Type | Single phase | Single phase | Three phase | Three phase |
| Speed Range | 1200~2900rpm | | | |









